

3900 Central Parkway
Hudsonville, MI 49426
toll free 800.338.7337
office 616.896.7100

techsupport@soundoffsignal.com
www.soundoffsignal.com

ADAPTOR KIT FOR ECVLM391(x) MARKER LIGHT ECVML39BMB

Your adaptor kit (ECVML39BMB) is designed to be used with the Series 390 marker light for replacement of incandescent marker lights with 1-1/2" screw centers and chassis ground.

INSTALLATION

1. Cut **WHITE** wire (-) to approximately half its length (2-1/2" to 3"). Strip insulation 1/4".
2. Install ring terminal and securely crimp to wire.
3. Insert **BLACK** wire through hole and gasket slit in adaptor.
4. Screw adaptor and gasket to vehicle using supplied screws making sure that ring terminal is installed as shown at right. **DO NOT OVERTIGHTEN SCREWS.**
5. Install light by carefully folding white wire and making sure it is fully contained in pocket in adaptor and then screw in place. **DO NOT OVERTIGHTEN SCREWS** as this may damage the light.

Technical Support: 1-800-338-7337

ECVLM391(x) MARKER
LIGHT WITH BULLET
CONNECTORS

RING TERMINAL

WHITE WIRE (-)

BLACK WIRE (+)

DISCARD

GASKET



ECVML39BMB
ADAPTOR KIT

WARRANTY

Except for our limited warranty, available on our website at www.soundoffsignal.com, a hard copy of which can be obtained from SoundOff Signal upon request, all other guarantees or warranties including the implied warranty of merchantability and the implied warranty of fitness for any particular purpose are void and of no effect, unless specifically agreed to in writing by SoundOff Signal